

## DTS-ES Discrete 6.1 and Dolby Digital EX with Power Amps for 7 Channels



#### ■ High-Quality Surround Sound Reproduction

- High Resolution 32bit Floating Point DSP
- 96 kHz Processing Circuit
- 3 Sets of Component Video Inputs
- 3 Sets of S-Video Switching

#### ■ Fully Discrete, Equal Power 7 Amplifier Channels, 75 Watts Each

|               |             |                                      |
|---------------|-------------|--------------------------------------|
| Front         | 75 W + 75 W | (8 ohms, 20 Hz - 20 kHz, 0.08 % THD) |
| Center        | 75 W        | (8 ohms, 20 Hz - 20 kHz, 0.08 % THD) |
| Surround      | 75 W + 75 W | (8 ohms, 20 Hz - 20 kHz, 0.08 % THD) |
| Surround Back | 75 W + 75 W | (8 ohms, 20 Hz - 20 kHz, 0.08 % THD) |

For optimum Dolby Digital and DTS reproduction, the AVR-1506 features high quality, wideband audio amplification, providing 75 watts power output for each of the 7 main channels. A large capacity power supply includes a high current power transformer along with discrete power output devices on all 7 amplifier channels for highest dynamic range and superb reproduction clarity.

#### ■ DENON's Basic Design for High-Quality Sound Reproduction

##### • Power Transformer for High Power Driven

The chassis that supports the large transformer has been designed to absorb vibration, and the transformer is housed inside a highly rigid frame to secure it more solidly to the chassis. In addition, a cushioning material has been placed around the core of the transformer to minimize interference on the signal and enable more faithful reproduction of the original sound. The AVR-1506 inherits these low-noise design from higher-end models not to mention the use of short ring.

##### • Twin Drive Rectifier

DENON's Twin Drive Rectifier design uses two rectifying diodes in parallel to bring out the maximum potential of the large transformer. Since the rectifiers recharge the large block capacitors at low impedance, they are able to supply ample current to reproduce deep basses as well as sudden bursts of sound from percussion or other musical instruments.

##### • Large Aluminum Extruded Heatsink

DENON uses large heatsink made of extruded aluminum. They have been placed in a design that ensures mostly uniform temperatures throughout the heatsink so that the output transistors for all channels can be driven under uniform conditions. This in turn ensures that all channels respond with equal performance to the demands of the audio signals.



#### ■ Wide-Range Play Capability for DVD-Audio and Super Audio CD

The power amp circuits of the AVR-1506 have been meticulously designed to reproduce the exceptionally high sound quality with wide frequency response from 10 Hz to 100 kHz.

#### ■ Dual Channel Surround Back Power Amp for 7.1 Surround

The AVR-1506 is equipped with a total of 7 power amps including 2 for the Surround Back channel speaker to give you more clearly defined sound localization at the rear for 6.1-channel surround sources such as DTS-ES Discrete 6.1, Dolby Digital EX, and DTS-ES NEO:6.

#### ■ Cinema Equalizer

The sound from movie sources recorded in Dolby Digital, DTS or other formats emphasizes high-frequency range due to a theater's front speakers being placed behind the movie screen. If this sound is reproduced in the home theater without correction, the high-frequency range is too strong. The AVR-1506 features a Cinema Equalizer to correct these high-frequency components so that the sound is clearer and easier to listen to. (For Dolby Digital, Dolby Pro Logic II, Dolby Digital EX and DTS surround modes)

#### ■ Assignable surround back (L/R) amplifiers for Multi-zone playback

Amplifiers initially reserved for Surround back (L/R) channels can be assigned to Zone 2 speakers.

#### ■ Personal Memory Plus, for Easy Operation

The AVR-1506 includes the Personal Memory Plus function that automatically remembers the surround mode you last used for each program source, so that you do not need to select the mode again for that program.

#### ■ Acclaimed Customization Feature

As with all of DENON's high-grade A/V receiver, the AVR-1506 lets you adjust parameters so that you can customize the performance of the AVR-1506 to suit your own home theater and enhance operating ease. The adjustments are easy to make via a dialog format on the fluorescent display on the front panel. These customized features are then stored, for each source input and surround mode, in Personal Memory Plus so constant readjustments are not required.

#### ■ Multi-Function Preset Memory Remote Controller with Glo-keys

#### ■ DENON's Latest Surround Technology Faithfully Recreates the Surround Sound Produced at the Dubbing Stage.

- DTS 96/24 Decoding for DVD-Video
- DTS-ES Discrete 6.1 and Matrix 6.1
- DTS NEO:6
- Dolby Digital EX
- Dolby Pro Logic IIx



# AVR-1506

## ■ 5 Channel/ 7 Channel Stereo Mode

DENON's popular 7 Channel Stereo mode transforms your favorite 2-channel sources such as CD, tape, stereo radio and stereo video sources into exciting surround sound, free of delay effects and unnatural artifacts, from all 7 speakers. This 7 Channel Stereo mode was originally developed by DENON to enhance music lovers' enjoyment with home theater ambience.

## ■ DENON DSP Surround Modes Add Listening Excitement

Put yourself in the middle of your favorite concert hall and music environments with DENON's DSP acoustic environment simulation modes. These DSP modes add spacious surround sound enhancements to your favorite music and video sources, and include these distinctly different sounding effects:

- |                         |               |
|-------------------------|---------------|
| 1. 5 / 7 Channel Stereo | 5. Video Game |
| 2. Virtual Surround     | 6. Matrix     |
| 3. Rock Arena           | 7. Mono Movie |
| 4. Jazz Club            |               |

## ■ Adjustable Cross-Over Switching

The AVR-1506 supports subwoofer cross-over switching with a choice of 8 cross-over frequencies: 40/60/80/100/120/150/200/250Hz. This lets you more accurately match the performance characteristics of the subwoofer to the main speaker system.

## ■ Component video circuits which maintain flat response up to 30 MHz, ensuring sharp image quality

### Other features

- Night Mode for not disturbing others
- Front Panel Inputs
- Front A/B Speaker Terminals
- High-grade Speaker Terminals (All ch)
- Remote In/Out Ports
- Frequency Synthesis Tuning
  - 56-Station AM/FM Random Preset Memory Tuning
  - Auto Preset Memory

### Input/Output Terminals For Every A/V System

#### Audio Inputs

- 8 Analog Inputs  
CD, (TUNER), DVD/VDP, TV/DBS, AUX, VCR, CDR/TAPE, V.AUX(FRONT)
- 6 Analog EXT. Input  
FRONT L/R, CENTER, SURROUND L/R, SUBWOOFER
- 4 Digital Input  
OPTICAL X 1  
COAXIAL X 2

#### Audio Outputs

- 1 Analog PRE OUT Terminals  
SUBWOOFER
- 2 Analog REC OUT Terminals  
VCR, CDR/TAPE

#### Video Inputs

- 4 Composite Inputs  
DVD/VDP, TV/DBS, VCR, V.AUX(FRONT)
- 3 S-Video Inputs  
DVD/VDP, TV/DBS, VCR
- 3 Component Inputs  
DVD/VDP, TV/DBS, VCR

#### Video Outputs

- 2 Composite Outputs  
VCR, MONITOR
- 2 S-Video Outputs  
VCR, MONITOR
- 1 Component Output  
MONITOR

### Specifications

#### Power Amplifier Section

|   |                              |  |
|---|------------------------------|--|
| Rated output *THD figures are power amp stage values. |                              |  |
| Front   | 75 W + 75 W<br>110 W + 110 W | (8 ohms, 20 Hz - 20 kHz, 0.08 % THD)<br>(6 ohms, 1 kHz, 0.7 % THD) |
| Center  | 75 W<br>110 W                | (8 ohms, 20 Hz - 20 kHz, 0.08 % THD)<br>(6 ohms, 1 kHz, 0.7 % THD) |
| Surround  | 75 W + 75 W<br>110 W + 110 W | (8 ohms, 20 Hz - 20 kHz, 0.08 % THD)<br>(6 ohms, 1 kHz, 0.7 % THD) |
| Surround Back   | 75 W + 75 W<br>110 W + 110 W | (8 ohms, 20 Hz - 20 kHz, 0.08 % THD)<br>(6 ohms, 1 kHz, 0.7 % THD) |

#### Preamplifier Section

|   |  |
|---|--|
| Input sensitivity/Impedance<br>V.AUX(FRONT) | CD, DVD/VDP, TV/DBS, VCR, CDR/TAPE, AUX<br>200 mV/47 kohms |
| Output level/Load impedance                 | SUBWOOFER 1.2 V/10 kohms<br>CDR/TAPE, VCR 200 mV/47 kohms  |
| Frequency response                          | 10 Hz - 100 kHz (+1, -3 dB) (Tone Defeat On)               |
| Signal-to-noise ratio                       | 98 dB (IHF-A weighted) (Tone Defeat On)                    |
| Tone control                                | Treble: ±12 dB at 10 kHz<br>Bass: ±12 dB at 100 Hz         |

#### FM Section

|                        |                   |
|------------------------|-------------------|
| Tuning frequency range | 87.5 - 107.9 MHz  |
| Usable sensitivity     | 1.0 µV (11.2 dBf) |

#### AM Section

|                        |                |
|------------------------|----------------|
| Tuning frequency range | 520 - 1710 kHz |
| Usable sensitivity     | 18 µV          |

#### General

|                   |  |
|-------------------|--|
| Power supply      | AC 120 V, 60 Hz  |
| Power consumption | 4.5 A  |
| Dimensions        | 17-3/32" (W) x 5-25/32" (H) x 16-9/64" (D)<br>434 (W) x 147 (H) x 417 (D) mm |
| Weight            | 11.3 kg, 24 lbs 15 oz  |



\*Design and specifications are subject to change without notice.  
 \*"Dolby", "Dolby Digital", "Pro Logic II", "Dolby Digital EX" and the double-D device are registered trademarks of Dolby Laboratories Licensing Corporation.  
 \*DTS is registered trademarks of DTS Technology.