


A/V Surround Receiver

AVR-3802**DENON****DTS-ES Discrete 6.1 and Dolby Pro Logic II with 7 Power Amps and Multi-room Flexibility**

The AVR-3802 provides two power amps for the Surround Back channels for a total of 7 fully-discrete amps of equal power. This powerful configuration lets you take maximum advantage of the dynamic performance that today's DTS-ES, Dolby Digital 6.1, DVD-Audio, and SACD program sources offer. The Dolby Pro Logic II features lets you hear 2-channel stereo sources in realistic 5.1-channel surround sound. The AVR-3802 includes Multi Zone Output and Power Amp Assign functions that let you output different sources to more than one room.



■ Fully Discrete, Equal Power Seven Amplifier Channels

Front	110 W + 110 W	(8 ohms, 20Hz - 20kHz, 0.05 % THD)
Center	110 W	(8 ohms, 20Hz - 20kHz, 0.05 % THD)
Surround	110 W + 110 W	(8 ohms, 20Hz - 20kHz, 0.05 % THD)
Surround back ...	110 W + 110 W	(8 ohms, 20Hz - 20kHz, 0.05 % THD)

The AVR-3802 features an equal power 7-channel amplifier section, with identical amplifier design on all 7 channels, with high current discrete output devices on all channels. Each of the 7 amplifier channels is rated at 110 watts, into 8 ohms, from 20 Hz - 20 kHz with no more than 0.05% THD.

■ Hefty Power Transformer for Stable Supply of Power

A huge power transformer has been connected in the power section where it is combined with a rectifier diode and a large block capacitor to ensure a large, stable supply of electrical current. Accordingly, the AVR-3802 boasts high output power of 110 W for each of the 7 channels.

■ High Power Custom Transistor

When temperatures rise or fall inside the unit, bias current values supplied to the power transistor tend to fluctuate, causing sound quality to deteriorate. The high power custom transistor used in the AVR-3802 ensures that the bias current is constantly uniform so that the sound you hear is of consistently stable, high quality.

■ DDSC-Digital, for High-quality Sound Reproduction

Featuring the Analog Devices SHARC 32-bit floating point DSP processor, DENON's DDSC-D circuitry faithfully recreates all the nuances of the original performance. Compared to ordinary 24-bit fixed point DSP processors, the Analog Devices SHARC 32-bit floating point DSP processor features greatly increased computational dynamic range for superior reproduction of stereo and multi-channel digital program sources.

■ Featuring DTS-ES Discrete 6.1 Decoding

The AVR-3802 is equipped with the DTS-ES (true discrete) 6.1 decoder, developed by DTS to provide dramatically improved surround sound panoramic reproduction and superior surround sound localization.

■ Supports DTS-ES Matrix 6.1 Decoding

■ Supports DTS NEO:6 Surround Decoding

■ Featuring Dolby Pro Logic II Decoding

Enjoy 2-channel stereo recordings in stunning 5.1-channel surround playback. The Dolby Pro Logic II decoder reproduces dynamic 5.1-channel surround sound not only from normal 5.1-channel DVD but from 2-channel sources such as videos and CDs, too. Dolby Pro Logic II uses matrix decoding technology that has been dramatically improved over Pro Logic. With Pro Logic II, for instance, the Surround (Rear) channels are in stereo (only mono with Pro Logic) and playback covers the full frequency range (only up to 7 kHz with Pro Logic). These improvements let you enjoy a wide variety of 2-channel sources with the exciting effects of 5.1-channel surround sound. In Dolby Pro Logic II, there is a Movie mode that creates a sound space suitable for movies, a Music mode that does the same for music, and a Pro Logic emulation feature that reproduces sound effects in the way that conventional Pro Logic does.

■ Dolby Digital Decoding

■ 96 kHz, 24-bit Audio D/A Converters

■ Digital Gain Control

The digital gain circuit controls the digital current in the area of the audio D/A converter. DENON has redesigned the digital gain circuit to improve the AVR-3802's signal-to-noise ratio and produce a cleaner signal for the speakers.

■ Adjustable Cross-Over Switching

The AVR-3802 supports subwoofer cross-over switching with a choice of 3 cross-over frequencies: 80, 100, and 120. This lets you more accurately match the performance characteristics of the subwoofer to the main speaker system.

■ Wide-Range Play Capability for DVD-Audio or SACD

■ 8-Channel Input For DVD-Audio or SACD

■ Surround A/B Speaker Switching

■ Support for Multi Zone Configurations

The AVR-3802 provides a Multi Zone Output function and a Select function that let you output different sources to multiple zones. Sources can be selected for output to up to 1 additional zone, in addition to the main room. Multi-room Zone can have variable pre-amp output.

The AVR-3802's Power Amplifier Assign function lets you assign the 2 Surround Back (SB L/R) amplifier channels to instead drive the Multi-room Zone powered speaker outputs, with 110 Watts per channel power output capability, while still providing 5 full amplifier channels to drive the main and surround speakers in the home theater room.

■ Personal Memory Plus

■ On Screen Display

■ Easy Operation with Programmable Remote Controller

• Dot Matrix LCD (10 characters)

Since the LC display on the remote controller is a dot matrix type, the characters are easier to read, and up to 10 characters can be displayed at any one time.

• System Call

System Call function to execute up to 29 successive pre-assigned commands at the single touch of a button.

• Preset Memory (Over 100 Built-in Codes)

Since the remote controller is preprogrammed with more than 100 remote control codes, you can use the AVR-3802's remote controller to operate not only DENON equipment but components made by other manufacturers as well. (Some components may not be supported by Preset Memory.)

• Back light

■ Frequency Synthesis Tuning

• 40-station AM/FM Random Preset Memory Tuning

• Auto Preset Memory

■ Other Features

• Cinema Equalizer

• Music Surround Modes Including 7/5-Channel Stereo

• "S" and Composite Video Switching

• Component Video Switching (2 inputs, 1 output)

• Tone Control

Input/Output Terminals For Every AV System

■ Audio Inputs

9 Sets Analog Input	PHONO, CD, TUNER, DVD, VDP, TV/DBS, VCR-1, VCR-2/V.AUX, CDR/TAPE
1 Set 8-ch Analog EXT. Input	FRONT L/R, CENTER, SURROUND L/R, SURROUND BACK L/R, SUBWOOFER
3 Sets Digital (Optical) Input	OPTICAL X 3
1 Set Digital (Coaxial) Input	COAXIAL

■ Audio Outputs

8 Sets Analog PRE Output	FRONT L/R, CENTER, SURROUND L/R, SURROUND BACK L/R, SUBWOOFER,
3 Sets Analog REC Output	VCR-1, VCR-2/V.AUX, CDR/TAPE
1 Set Analog Multi Zone Output	L/R
1 Set Digital (Optical) Output	OPTICAL

■ Video Inputs

2 Sets Component Video Input.....	DVD, TV/DBS
5 Sets Composite Input	DVD, VDP, TV/DBS, VCR-1, VCR-2/V.AUX
5 Sets S-Video Input	DVD, VDP, TV/DBS, VCR-1, VCR-2/V.AUX

■ Video Outputs

1 Set Component Video Output	MONITOR
3 Sets Composite Output	VCR-1, VCR-2/V.AUX, MONITOR
3 Sets S-Video Output	VCR-1, VCR-2/V.AUX, MONITOR

Specifications

■ Power Amplifier Section

Rated output	*THD figures are power amp stage values.	
Front	110 W + 110 W	(8 ohms, 20Hz - 20kHz, 0.05 % THD)
	150 W + 150 W	(6 ohms, 1 kHz, 0.7 % THD)
Center	110 W	(8 ohms, 20Hz - 20kHz, 0.05 % THD)
	150 W	(6 ohms, 1 kHz, 0.7 % THD)
Surround	110 W + 110 W	(8 ohms, 20Hz - 20kHz, 0.05 % THD)
	150 W + 150 W	(6 ohms, 1 kHz, 0.7 % THD)
Surround back	110 W + 110 W	(8 ohms, 20Hz - 20kHz, 0.05 % THD)
	150 W + 150 W	(6 ohms, 1 kHz, 0.7 % THD)

■ Preamplifier Section

Input sensitivity/impedance	
PHONO(MM)	2.5 mV/47 kohms
CD, DVD, VDP, TV/DBS, VCR-1, VCR-2/V.AUX, CDR/TAPE	
FRONT L/R, CENTER, SURROUND L/R, SURROUND BACK	200 mV/47 kohms
SUBWOOFER	200 mV/15 kohms
Output level/Load impedance	
FRONT L/R, CENTER, SURROUND L/R, SURROUND BACK L/R, SUBWOOFER	
MULTI ZONE L/R	1.2 V/10 kohms
VCR-1, VCR-2/V.AUX,	
CDR/TAPE	200 mV/47 kohms
Frequency response	10 Hz - 100 kHz; +0, -3 dB
Signal-to-noise ratio	102 dB
RIAA deviation	±1 dB (20 Hz - 20 kHz)
Tone control	Treble: ±10 dB at 10 kHz, Bass: ±10 dB at 100 Hz

■ FM Section

Tuning frequency range	87.5 - 107.9 MHz
Usable sensitivity	1.0 μV (11.2 dBf)

■ AM Section

Tuning frequency range	522 - 1710 kHz
Usable sensitivity	18 μV

■ General

Power supply	AC 120 V, 50 Hz
Power consumption	7.1 A
Dimensions	434 (W) x 171 (H) x 416 (D) mm
	17.1" (W) x 6.7" (H) x 16.4" (D)
Weight	16.5 kg, 36.4 lbs



*Design and specifications are subject to change without notice.
 "Dolby", "Dolby Digital", "Pro Logic II", and the double-D device are registered trademarks of Dolby Laboratories Licensing Corporation.
 "DTS", "DTS-ES Extended Surround" and "Neo:6" are trademarks of Digital Theater System, Inc.

DENON ELECTRONICS
 DIVISION OF DENON CORPORATION (USA)
 19 CHAPIN ROAD, P.O. BOX 867, PINE BROOK, NJ 07058-9777 USA
 TEL: 973-396-0810 www.denon.com

DENON CANADA INC.
 17 DENISON STREET, MARKHAM ONTARIO, CANADA L3R 1B5
 TEL: 905-475-4085 www.denon.ca

NIPPON COLUMBIA CO., LTD.
 14-14, AKASAKA 4-CHOME, MINATO-KU, TOKYO 107-8011, JAPAN