

AVR-3312

Integrated Network AV Surround Receiver

DENON

100th
Anniversary
since 1910

www.denon100.com

Support AirPlay and Network Functions

The AVR-3312 has built-in AirPlay, and includes network functions that let you enjoy a wide variety of on-line digital content. It is also equipped with AL24 Processing Plus and Clock Jitter Reducer technology to dramatically improve sound quality, and a high-performance I/P converter and scaler to give you optimum picture quality. The AVR-3312 has been specifically designed to give you the ultimate experience in today's state-of-the-art home entertainment.



Network flickr last.fm RDS RadioTEXT HDMI CNSV
 DOLBY TRUEHD PRO LOGIC IIz DTS-HD Master Audio AUDYSSEY DYNAMIC VOLUME AUDYSSEY DSX 3D D-D.S.C.-HD AL24 Processing Plus Multi Zone PERSONAL MEMORY Plus



January 2012

Features

New Features

- AirPlay built in
- Supports "Denon Remote App" to simplify operation by an iPhone/ iPod touch
- Internet Radio and Preset buttons, for quick, easy enjoyment of Internet radio
- Four quick select buttons, quick access to frequently-used video or music sources
- Setup Wizard, providing easy-to-follow setup instructions
- Easy operation, Graphical User Interface with overlay on HD sources
- 7-HDMI inputs and 2-output (Simultaneous)

State-of-the-art Denon Solutions for Maximising Content Quality

- Fully discrete, identical quality and power for all 7 channels (165 W x 7 ch)
- Stable power supply for high-quality sound and picture playback
- Dynamic Discrete Surround Circuit, D.D.S.C.-HD
 - AL24 Processing Plus, to dramatically enhance the music listening experience
- Clock Jitter Reducer
- Supports HDMI (with 3D, Audio Return Channel) Deep Color, "x.v.Color", Auto Lipsync and HDMI control function
- High definition audio support, Dolby TrueHD and DTS-HD Master Audio
- Audyssey DSX processing
- Supports Dolby Pro Logic IIz processing
- Dual subwoofers preout
- Extended picture adjustment possibilities
- I/P Converter and Scaler up to 1080p

Connectivity & Future-ready Expandability

- Enhanced network capability⁽¹⁾
 - Internet Radio and network audio/photo streaming via Ethernet
 - Last.fm and Flickr online support
 - 'Party Mode Plus'
 - FLAC HD, High-resolution audio format
 - Compatible with Windows 7
 - web control
- Direct play for iPod and iPhone via USB
- Power Amp Assign function, for versatility in using the AVR-3312 for different purpose (Surround Back, Front Height, Zone 2 & 3, Bi-Amp, Front Speaker B)

Ease-of-Use

- Audyssey Dynamic Volume for real-time volume adjustment
- Audyssey MultEQ XT and Auto Setup

Others

- Low power consumption at stand-by of 0.1W
- Control4, AMX or Crestron third party control support

More Features

- **Fully discrete, identical quality and power for all 7 channels (165 W x 7ch)**

To faithfully reproduce the original surround sound, each of the AVR-3312's 7 channels is equipped with the same power amp of equal power. Since these power amps also use discrete rcuits configured with parts strictly selected for their contribution to high sound quality, rather than with low-cost integrated circuits (ICs), the surround sound playback is of impeccably high quality.



- **Featuring 3D pass-through technology**

By connecting a 3D-compliant Blu-ray disc player and 3D-compliant TV to the AVR-3312, you will have a 3D home theatre where you can enjoy high-definition sound and video on a level you've never experienced before.

- **Minimum Signal Path for clear audio and video signal**

The "simple and straight" design concept has been thoroughly implemented in the signal paths to contribute to immaculately clean audio and video playback. Signal paths are as short as possible to keep signal degradation in the audio and video circuitry to an absolute minimum.

- **AL24 Processing Plus**

The acclaimed AL24 Processing Plus processing improves the fidelity of 2ch and multi channel PCM sources by sophisticated DSP

processing algorithms that improves low level detail and enhances fidelity by adaptive filtering techniques. AL24 Processing Plus also provides increased dynamic range and spatial information, bringing out all the nuances with optimum clarity and natural fidelity.

- **Compressed Audio Restorer to enhance digital music files**

Denon's audio technology for MP3, WMA and MPEG-4 AAC compressed format to reproduce higher frequency range and deeper bass sound. This technology provides better sound for internet radio, iPod or iPhone.

- **Denon Remote App**

The Denon Remote App available for free on iTunes App store transfers your iPhone or iPod touch in a nice remote control supporting the key features of the AVR. But it doesn't stop here as you can control the network audio streaming from your PC and internet radio function supported by cover art. That's ease of use, that's fun.



- **Support AirPlay and Network Functions**

When connected to a network, the AVR-3312 can play audio files and still images such as photographs that are stored on your computer. You can also listen to internet radio and a host of other online music sources that use network technology. The AVR-3312 also supports AirPlay that lets you stream your music library from an iPhone, iPad, iPod touch, or iTunes.

- **Picture Adjust**

You can adjust the picture quality and reduce any noise appearing on the TV. (Contrast, Brightness, Chroma level, Hue, Reduce overall picture noise, Emphasise picture contours).

- **Advanced Graphical User Interface (GUI) overlay on HDMI**

This nice function let you keep the full overview even while watching a movie. Just check your settings or get the volume and surround mode indication overlaid on the film you watch. Don't miss any scene.



*An image of OverLay GUI

- **3 source / 3 zone output + 2 dedicated preout**

The AVR-3312 lets you enjoy a program source in the Main Zone (the room where the AVR-3312 is located) and in Zone 2 and Zone 3 (another room). The source can be the same for both zones, or you can enjoy different sources in those zones if you prefer. The AVR-3312 even has a separate preamp for Zone 2 or Zone 3 that lets you connect an independent power amp in that room.

- **Phono input**

- **7.2 ch preout**

- **11 ch Speaker terminals**

- **Direct Mechanical Ground Construction**

- **Digital audio into zone preout**

- **Zone 2 Video output**

- **2-line fluorescent display on front panel**

- **Pre memory remote control handset with Glow-Key**

- **Remote Setup Guidance**

- **Auto surround mode**

- **Sleep timer function**

- **Audio Delay function (0 to 200 msec)**

- **Muting level settings (Full / -40 dB / -20 dB)**

- **Audio level memory, capable of correcting different signal levels for each input device**

- **Variable subwoofer crossover switching**

- **Two Trigger outputs (150 mA)**

*1) Requires contract with Internet service provider.

Main Specifications

Power amplifier section		Preamplifier section	
Rated output	*THD figures are power amp stage values.	Input sensitivity/impedance	200 mV / 47 kΩ/kohms
Front L/R	125 W + 125 W (8 ohms, 20 Hz - 20 kHz, THD 0.05 %) 165 W + 165 W (6 ohms, 1 kHz, THD 0.7%)	Frequency response	10 Hz - 100 kHz - +1, -3 dB DIRECT mode)
Centre	125 W (8 ohms, 20 Hz - 20 kHz, THD 0.05 %) 165 W (6 ohms, 1 kHz, THD 0.7%)	S/N Ratio	102 dB (IHF-A weighted, DIRECT mode)
Surround L/R	125 W + 125 W (8 ohms, 20 Hz - 20 kHz, THD 0.05 %) 165 W + 165 W (6 ohms, 1 kHz, THD 0.7%)	FM section	
Surround Back L/R	125 W + 125 W (8 ohms, 20 Hz - 20 kHz, THD 0.05 %) 165 W + 165 W (6 ohms, 1 kHz, THD 0.7%)	Tuning frequency range	87.5 - 108 MHz
		AM section	
		Tuning frequency range	522 - 1611 kHz
General			
		Power supply	AC 230 V, 50 Hz
		Power consumption	670 W (Standby 0.1 W, CEC Standby 2.2 W)
		Dimensions (W x H x D)	434 x 167 x 382 mm
		Weight	11.8 kg



Denon Europe
Division of D&M Germany GmbH
An der Kleinbahn 18
41334 Nettetal, Germany
Tel.: 0049 2157 1208-0
Fax: 0049 2157 1208-10

www.denon.eu

www.denon.eu

Ports

IN			
IN	HDMI (included front 1)	x 7	
	Component	x 2	
	S-Video	x 2	
	Composite (video) (included front 1)	x 5	
	Analogue Audio (included front 1)	x 8	
	Digital Optical	x 2	
	Digital Coaxial	x 2	
	Phono	x 1	
	OUT	HDMI Monitor	x 2
		Component	x 1
Composite Monitor (incl. Zone 2 Video)		x 3	
Audio Preout (FL/ FR/ C/ SL/ SR/ SBL/ SBR/SW)		7.2ch	
Audio Preout (L/R for Zone 2 & 3)		x 2	
OTHER	Audio Recout (L/R)	x 1	
	Phones	x 1	
	Ethernet	x 1	
	USB port	x 1	
	Microphone Port	x 1	
	Dock Control Port	x 1	
	FM Tuner Antenna	x 1	
	AM Tuner Antenna	x 1	
Remote Control In/Out	In 1/Out 1		
RC232C	x 1		
DC12V 150mA MAX. trigger out	x 2		

EAN

AVR3312BKE2 4582116366394

* Design and specifications are subject to change without notice.
* "Dolby", "Pro Logic" and the double-D symbol are trademarks of Dolby Laboratories.
* DTS is a registered trademark and the DTS logos, Symbol, DTS-HD and DTS-HD Master Audio are trademarks of DTS, Inc.
* HDMI, the HDMI logo and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC.
* Windows Media and the Windows logo are trademarks or registered trademarks of Microsoft Corporation in the United States and/or other countries.
* NSV is a registered trademark of Analog Devices, Inc.
* Audyssey MultEQ XT is a registered trademark of Audyssey Laboratories. Audyssey Dynamic EQ is a registered trademark of Audyssey Laboratories. Audyssey Dynamic Volume is a registered trademark of Audyssey Laboratories.
* "Made for iPod," "Made for iPhone," and mean that an electronic accessory has been designed to connect specifically to iPod, or iPhone, respectively, and has been certified by the developer to meet Apple performance standards. Please note that the use of this accessory with iPod, or iPhone, may affect wireless performance.
* Apple is not responsible for the operation of this device or its compliance with safety and regulatory.
* "AirPlay", the AirPlay logo, iPhone, iPod classic, iPod nano, iPod shuffle, iPod touch and iTunes are trademarks of Apple Inc., registered in the U.S. and other countries.
Denon is a trademark or registered trademark of D&M Holdings, Inc.